

WLM-531D Audio Level Meter & Alarm



WLM-531D Audio Level Meter & Alarm

입력되는 5CH+3CH의 Digital Audio 신호(AES/EBU)의 Level을 54 dot의 LED Bar Graph Meter를 통하여 표시한다. 3CH의 입력신호에 대해서는 무음감지에 의한 Alarm기능을 제공하는데 각 CH별로 ON/OFF의 선택이 가능하며, 각각 16 단계로 선택이 가능한 무음감지 Level과 시간은 3CH에 대하여 공통으로 적용된다.

또한 8CH Audio 신호의 입력에는 각각 Through Output용 커넥터와 Dummy 스위치가 장착되어 있어 시스템 구성에 따라 다양하게 사용할 수 있다.



Rear View (WLM-531D)

Features

- 8CH AES/EBU Input (Balanced)
- 8CH AES/EBU Output (Balanced, Through Output)
- 54 dot LED Bar Graph Meter (Peak & RMS Display)
- Low Level Detect에 의한 Alarm (3CH)
- Detect Enable/Disable (each CH)
- Detect Level Set (16 Step)
- Detect Time Set (16 Step)
- Alarm On/Off & Reset
- Redundant Power Supply (Free Voltage)

Ordering Information

- ✓ WLM-531D Main Frame

Technical Specification

Audio Input

Type AES/EBU
Channel 8CH (Through Output)
Impedance 110Ω, Balanced

Level Meter

Resolution 54 dot
Vertical Disp. 5CH
Horizontal Disp. 3CH
Type Peak & RMS

Control Data

Remote 1Port, RS-422
APC 1Port, RS-422 & Ethernet

General

Power AC 100~240V 50/60Hz
WLM-531D 482(W) x 132.5(H) x 270(D)mm